



IMPORTANT NOTE:

The DC HW with Audio Line-In features a car adapter plug (not shown) integrated into the power-end of this kit. You must clip the car adapter portion off to expose the red and white wires to allow for the discussed hardwiring within this document. Please make sure your power source or battery is disconnected before wiring your DC HW kit.

**Auto Start Stop - Firmware v44 and above
(Adjustable from XD1080 Advanced Text File)**

The DC HW with Audio Line-In can utilize the APSS and PDD feature in Firmware v44 and above. Download available here: <http://replayxd.com/support/download/replay-xd1080-firmware-single-update>

APSS: Auto Power Start Stop

APSS is set to Off by default, you can set it to On to allow the camera to auto Power-on and Start-record after external power is applied to the camera.

PDD: Power Down Delay

PDD is only active when APSS is set to On. You can adjust the Power Down Delay to allow the camera to Stop-record and Power-off after external power has been interrupted.